

12G-SDI to HDMI 2.0 Converter with Audio Ext.

User Manual

500744



Table of Contents

1. Safety Precautions.....	3
2. Introduction.....	4
3. Features.....	4
4. Package Contents.....	4
5. Specifications.....	5
6. Panel Description.....	6
7. Supported Resolutions.....	6
8. Application Diagram.....	7

1. Safety Precautions

To ensure the best performance from the product, please read all instructions carefully before using the device. Save this manual for future reference.

- Follow basic safety precautions to reduce the risk of fire, electrical shock, and injury.
- Do not dismantle the housing or modify the module. It may result in electrical shock or burns.
- Do not open or remove the housing of the device as you may be exposed to dangerous voltage or other hazards.
- To prevent fire or shock hazard, do not expose the unit to rain, moisture and do not install this product near water. Keep the product away from liquids.
- Spillage into the housing may result in fire, electrical shock, or equipment damage. If an object or liquid falls or spills on the housing, unplug the module immediately.
- Do not use liquid or aerosol cleaners to clean this unit. Always unplug the power to the device before cleaning.
- Using supplies or parts not meeting the product specifications may cause damage, deterioration or malfunction.
- Refer all servicing to qualified service personnel.
- Install the device in a place with adequate ventilation to avoid damage caused by overheat.
- Unplug the power when left unused for a long period of time.
- Information on disposal of devices: do not burn or mix with general household waste, please treat them as normal electrical waste.

Copyright Notice

All contents in this manual are copyrighted, and cannot be cloned, copied, or translated without the express permission of MuxLab Inc. Product specifications and information in this document are for reference only, and the content may be updated from time to time without prior notice.

2. Introduction

The 12G-SDI to HDMI 2.0 converter with audio extension. (model: 500744) provides a cost-effective way to convert 12G/6G/3G/HD-SDI signals to HDMI 2.0 compatible format. The conversion between SDI and HDMI is purely digital and guarantees a lossless transformation for both audio and video. The device supports up to 8-channel audio and also provides a low-jitter SDI local loop and high-quality analog stereo output to provide flexibility to users.

3. Features

- Supported high-definition (HD) formats
- Auto 12G/6G/3G/HD-SDI detection
- Support HDMI 2.0 & below
- Supports stereo audio output
- Supports one SDI compliant input, one HDMI compliant output & one SDI loopout

4. Package Contents

- One (1) 12G-SDI to HDMI 2.0 Converter with Audio Ext.
- One (1) 5VDC Power Adapter
- One (1) Rack-mounting ears set
- One (1) User manual (available via download)

Notes: Confirm that the product and accessories are all included. If not, please contact the supplier from which you purchased the unit.

5. Specifications

Technical	
SDI standards	12G/6G/3G/HD-SDI
HDMI standards	HDMI 2.0
Auto 12G/6G/3G/HD-SDI detection	Yes
Video bandwidth	[SDI] 11.88 Gbps, 11.88/1.001 Gbps [HDMI] up to 18Gbps
Video support	[12G] 4K/50/59.94/60Hz [6G] 4K/23.98/24, 25, 29.97, 30Hz [3G] 1080p50/59.94/60 [HD] 720p/50/59.94/60Hz, 1080i/50/59.94/60Hz, 1080p/23.98/24/25/29.97/30Hz [HDMI] up to 4K/60
Input signal	1 x SDI
Output signal	1 x HDMI + 1 x SDI + 1 x 3.5mm (Audio)
Output impedance (SDI)	75Ω
Synchronization mode	Internal synchronization or external synchronization
Eye pattern characteristics	[12G-SDI] Timing jitter: 0.29 UI, Alignment jitter: 0.13 UI [6G-SDI] Timing jitter: 0.18 UI, Alignment jitter: 0.06 UI [3G-SDI] Timing jitter: 0.09 UI, Alignment jitter: 0.03 UI
Cable equalization	[12G-SDI] up to 80m [6G-SDI] up to 100m [3G-SDI] up to 190m [HD-SDI] up to 300m
Audio support	[Analog] Supports 2ch [SDI] Surround sound (up to 7.1ch)
Input	1 x BNC [SDI]
Output	1 x HDMI + 1 x BNC [SDI] + 1 x 3.5mm Stereo Jack
BNC connector	75Ω inter-locked socket
HDMI connector	Type A [19-pin female]
Mechanical	
Housing	Metal enclosure
Dimensions [L x W x H]	92mm x 45mm x 23mm [3.7" x 1.8" x 0.9"]
Weight	175g [6.2oz]
Power supply	5VDC
Power consumption	4 Watts [max]
Operation temperature	0~40°C [32~104°F]
Storage temperature	-20~60°C [-4~140°F]
Relative humidity	20~90% RH [no condensation]
General	
Warranty	2 years
Order Information	500744 12G-SDI to HDMI 2.0 Converter with Audio Ext. (UPC: 627699007440)

6. Panel Description



1. **SDI IN:** 12G/6G/3G/HD-SDI Input
2. **LED:** Signal LED indicator
3. **SDI OUT:** 12G/6G/3G/HD-SDI loopout
4. **LED:** Power LED indicator
5. **HDMI OUT:** HDMI 2.0 Output.
6. **Stereo Audio:** Stereo Analog Output
7. **5V DC:** Connect to a 5VDC power supply.

7. Supported Resolutions

12G-SDI Output	
4K2K @50/59.94/60Hz	SMPTE ST-2082
6G-SDI Output	
4K2K @23.98/24, 25, 29.97, 30Hz	SMPTE ST-2081
3G-SDI Output	
1080p @ 50/ 59.94 / 60Hz	SMPTE 424M, SMPTE 425M
HD-SDI Output	
720p @ 50Hz	SMPTE 296M -3
720p @ 60 / 59.94Hz	SMPTE 296M -1, -2
1080i @ 50Hz	SMPTE 274M -6
1080i @ 60 / 59.94Hz	SMPTE 274M -4, -5
1080p @ 24 / 23.98Hz	SMPTE 274M -10, -11
1080p @ 25Hz	SMPTE 274M -9
1080p @ 30 / 29.97Hz	SMPTE 274M -7, -8

8. Application Diagram

