



# 115WH LITHIUM AC POWER PACK 160W

MODEL NO: **SPB160W.V2**

Thank you for purchasing a Sealey product. Manufactured to a high standard, this product will, if used according to these instructions, and properly maintained, give you years of trouble free performance.

**IMPORTANT:** PLEASE READ THESE INSTRUCTIONS CAREFULLY. NOTE THE SAFE OPERATIONAL REQUIREMENTS, WARNINGS & CAUTIONS. USE THE PRODUCT CORRECTLY AND WITH CARE FOR THE PURPOSE FOR WHICH IT IS INTENDED. FAILURE TO DO SO MAY CAUSE DAMAGE AND/OR PERSONAL INJURY AND WILL INVALIDATE THE WARRANTY. KEEP THESE INSTRUCTIONS SAFE FOR FUTURE USE.



Refer to instructions



Keep in dry area protect from rain



Electrical shock hazard



Warning: explosive material

## 1. SAFETY

### 1.1. ELECTRICAL SAFETY FOR USE OF POWER PACK

- WARNING!** It is the user's responsibility to read, understand and comply with the following electrical instructions: You must ensure the risk of electric shock is minimised by the installation of appropriate safety devices.
- ✓ You must also read and understand the following instructions concerning electrical safety. The Electricity At Work Act 1989 requires all portable electrical appliances, if used on business premises, to be tested by a qualified electrician, using a Portable Appliance Tester (PAT).
- ✓ The Health & Safety at Work Act 1974 makes owners of electrical appliances responsible for the safe condition of the appliance and the safety of the appliance operator. If in any doubt about electrical safety, contact a qualified electrician. You must ensure that you:
  - ✓ Inspect the Power Pack, charge cables and connectors for wear and damage to ensure items are safe before use. If worn or damaged **DO NOT** use.
  - ✓ Uncoil used cables between Power Pack and devices when in use.
  - ✓ **DO NOT** pull the Power Pack from any sockets by the lead used.
  - × **DO NOT** try to take the Power Pack apart.
  - × **DO NOT** get the Power Pack wet, or use in wet, damp conditions (for indoor use only).
- WARNING!** Modern vehicles contain extensive electronic systems. You are required to check with the vehicle Manufacturer, for any specific instructions regarding the use of this type of equipment on each vehicle. No liability will be accepted for damage / injury, where this product is not used in accordance with all instructions.

### 1.2. BATTERY SAFETY

- ✓ Recycle or dispose of used battery as stipulated by local regulation.
- ✓ Ensure the internal battery is fully charged before initial use.
- WARNING!** To reduce the risk of burns or fire:
  - × **DO NOT** attempt to open, disassemble, modify or service the battery pack.
  - × **DO NOT** crush, puncture, short external contacts or dispose of in fire or water.
  - × **DO NOT** expose to temperatures above 60°C (140°F).
  - × **DO NOT** move/handle/use the Power Pack when it is being charged.
  - × **DO NOT** leave battery in a discharged state, recharge battery immediately. Before storage, fully recharge the battery, subsequently recharge the battery at least once every three months of non-use.

### 1.3. GENERAL SAFETY INSTRUCTIONS

- ✓ Familiarise yourself with the application and limitations of the Power Pack as well as the potential hazards.
- ✓ Keep children and unauthorised persons away from the working area.
- ✓ When not in use, store carefully in a safe, dry, childproof location.
- ✓ Use the cables provided with this unit only.
  - × **DO NOT** short circuit this unit and keep it away from metal objects such as coins, keys, jewellery etc.
  - × **DO NOT** pull the cables or clamps from any connections.
  - × **DO NOT** use the unit outdoors, or in damp, or wet locations and **DO NOT** operate within the vicinity of flammable liquids or gases.
  - × **DO NOT** use for a task for which it is not designed.
  - × **DO NOT** modify or disassemble the Power Pack.
  - × **DO NOT** drop unit. If unit receives a sharp blow or is otherwise damaged in any way have it checked by a qualified technician.

**NOTE:** This appliance can be used by children aged from 8 years and above and persons with reduced physical, sensory or mental capabilities or lack of experience and knowledge if they have been given supervision or instruction concerning use of the appliance in a safe way and understand the hazards involved. Children shall not play with the appliance. Cleaning and user maintenance shall not be made by children without supervision.

## 2. INTRODUCTION

Powered by lithium-ion technology. Easily fits in a glove box or backpack, weighing at 1.5kg. Multiple high amperage outputs. Fitted with a 115Wh battery. This unit can also supply multiple full charges to batteries in the Sealey 20V, 14V and 12V power tool ranges. Supplies several full charges for smartphones (e.g. iPhone ; seven charges and Samsung Galaxy ; six charges) or two full charges for your tablet/laptop (based on an 8800mAh battery) as well as many other devices. Fully charges in 8 hours with an 18W fast charger (not included). Supplied with Type-C charging cable. Includes a small integral work light. Inputs: 2 x Bi-Directional Type-C (5V DC 2A, 9V DC 2A,12V DC1.5A). Outputs: 230V~50HZ AC, 2 x 12V 8A DC Outputs (100W MAX.), Standard USB 5V DC 2A, QC3.0 USB (5V DC 2A, 9V DC 2A,12V DC1.5A), 3 x Type-C Outputs (5V DC 2A, 9V DC 2A,12V DC1.5A).

## 3. SPECIFICATION

Model No.:.....SPB160W.V2  
 Inputs: ..... 2 x Bi-Directional TYPE-C  
 Outputs: .....  
 230V~50Hz AC, 2 x 12V 8A DC Outputs (100W Max), Standard USB 5V DC 2.1A, USB QC3.0 (5V DC 2.1A, 9V DC 2.1A,12V DC 1.5A), Type-C output (5V DC2.1A, 9V DC 2.1A,12V DC 1.5A)  
 Capacity:..... 115Wh Lithium Battery  
 Accessories: ..... USB Type-C Cable, DC Car Socket Adaptor  
 Charge Times:..... 8hrs on 18W Fast Charge  
 Dimensions (W x D x H):..... 263 x 115 x 40mm

## 4. OPERATION

1	LED Charge Indicator
2	Dual 12V DC Output
3	5V/2.1A USB Output
4	USB Output (QC3.0)
5	TYPE-C Output
6	LED Light
7	Bi-Directional TYPE-C 1
8	Bi-Directional TYPE-C 2
9	Power button



fig.1

### 4.1. CHARGING THE POWER PACK

- 4.1.1. Using the TYPE-C Charging cable included, insert the cable in either port (fig 1.7 or 1.8). Connect the other end of the cable into either a USB-A Plug adapter (not supplied), car accessory charger (not supplied) or directly into a wall mounted USB-A output.
- 4.1.2. While charging, the LED charge indicator (fig.1.1), will display battery level. One light lit indicates 0-20%, all five lights lit indicate 80-100%. Once fully charged, the unit will switch off.

### 4.2. USING THE POWER PACK

- 4.2.1. To charge USB digital devices, select appropriate cable for your device. Plug the charging cable into any of the 2 USB-A outputs (Fig 1.3 and fig 1.4) or 3 USB TYPE-C outputs (Fig 1.5, Fig 1.6 or Fig 1.7). Disconnect after use.
- 4.2.2. To use the DC 12V output, plug the car accessory socket cable into the DC output port (fig.1.2) and insert charger (not supplied) into the accessory socket.
- 4.2.3. Disconnect after use.
- 4.2.4. Insert a suitable 3 pin plug into the AC output while ensuring the device is within the recommended wattage.
- 4.2.5. Press and hold the power button (fig.1.9) down for 3 seconds to turn on the AC output.
- 4.2.6. When finished with this feature, press and hold the power button to turn off the AC output.
- 4.2.7. Disconnect after use.

### 4.3. LED WORK LIGHT

- 4.3.1. Double press the power button (fig.1.9) to turn LED on.
- 4.3.2. Press the power button when LED is lit to change between three modes (Normal, SOS and Strobe).
- 4.3.3. Double press the power button to turn the LED off.

## 5. MAINTENANCE

- 5.1. After usage recharge the unit.
- 5.2. After charging / usage remove all cables / connections.
- 5.3. Use a clean, dry cloth to wipe down the unit after use.
- 5.4. Store in clean, dry environment with ambient temperature between 4°C and 30°C.

Parts support is available for these products. Please email [sales@sealey.co.uk](mailto:sales@sealey.co.uk) or telephone 01284 757500



#### ENVIRONMENT PROTECTION

Recycle unwanted materials instead of disposing of them as waste. All tools, accessories and packaging should be sorted, taken to a recycling centre and disposed of in a manner which is compatible with the environment. When the product becomes completely unserviceable and requires disposal, drain any fluids (if applicable) into approved containers and dispose of the product and fluids according to local regulations.



REGISTER YOUR  
PURCHASE HERE



#### WEEE REGULATIONS

Dispose of this product at the end of its working life in compliance with the EU Directive on Waste Electrical and Electronic Equipment (WEEE). When the product is no longer required, it must be disposed of in an environmentally protective way. Contact your local solid waste authority for recycling information.



#### BATTERY REMOVAL

Under the Waste Batteries and Accumulators Regulations 2009, Jack Sealey Ltd are required to inform potential purchasers of products containing batteries (as defined within these regulations), that they are registered with Valpak's registered compliance scheme. Jack Sealey Ltd's Batteries Producer Registration Number (BPRN) is BPRN00705.

**Note:** It is our policy to continually improve products and as such we reserve the right to alter data, specifications and component parts without prior notice. Important: No Liability is accepted for incorrect use of this product.

**Warranty:** Guarantee is 12 months from purchase date, proof of which is required for any claim.

Sealey Group, Kempson Way, Suffolk Business Park, Bury St Edmunds, Suffolk. IP32 7AR



01284 757500



[sales@sealey.co.uk](mailto:sales@sealey.co.uk)



[www.sealey.co.uk](http://www.sealey.co.uk)