




**GALAXY**  
Wireless Bluetooth Speaker



**Contents:**



Bluetooth speaker X 1



Type-C Charging Cable X 1



User manual X 1





Thank you Note

1

**Power On/Off**

1. Previous/Volume-
2. Next/Volume+
3. Play/Pause and Mode switching

4. Power button/ Light mode switch
5. TF card slot
6. Charging port



2

**Power On/Off**

1. Long press the power button for three seconds to turn on;
2. Long press the power switch for three seconds to turn off.

**Bluetooth connection**

1. Turn on the Bluetooth speaker, the breathing light flashes slowly.
2. Then turn on the Bluetooth of your phone and search for "iGear GALAXY". Click manually to connect.
3. The speaker can automatically reconnect to the last paired device. So when the Bluetooth of your device turns on, (Just turn on the speaker), it will automatically reconnect.

**Answer incoming calls**

Press the power button to answer the incoming call.

**Reject incoming calls**

Long press the power button for 2sec to reject the incoming call.

3

**End call**

Press the power button once to end the ongoing call.

**Redial calls**

Press the power button twice to redial the last call.

**Mode Switching**

Long press the play/pause button to switch between modes (Bluetooth/ TF card /FM)

**Light modes**

Short press the power button to switch between four lighting modes.

**TF card mode**

Simply insert the TF card into the slot and the device will automatically recognize and play the music stored in it.

**Clear pairing records**

Press the previous/volume high(+) button three times to clear the pairing records

4

**FM mode**

1. Long press the play/pause button to switch on the FM mode.

Note: Insert the Type-C cable into the charging slot as an antenna for better reception.

2. Press the play/pause button twice to activate auto channel search

3. Press the play/pause button twice for 2 seconds to stop the search

4. Long press the "+"/"-" to select the desired channel

**Direction to play music**

1. Short press the play/pause button to Play/pause music

2. Long press the "-" button for previous song

3. Long press the "+" button for next song

4. Short press the "-" button in order to decrease Volume

5. Short press the "+" button in order to increase Volume

5

**True Wireless Stereo (TWS)**

You can connect two iGear Galaxy speakers as a pair for stronger stereo and surrounding sound effect.

1. Make sure the Bluetooth function is OFF on your smartphone/media player;

2. Turn on two iGear Galaxy speakers;

3. Press the play/pause button twice on one of the speakers. There will be a "dong" Sound.

Wait for about 1 minute after the prompt, there will be a "TWS Pairing complete" prompt when the pairing is successful

4. Then turn On the Bluetooth of your smartphone/media player and search for "iGear Galaxy". to connect

5. To disconnect the TWS function, double click the play/pause button.

**Charging**

1. As the product has a built-in non-removeable and rechargeable battery, we recommend to use the Type-C cable provided with the speaker

2. The power LED lights up red while charging and goes off when charging is complete

6

**Specifications**

Bluetooth version: V5.3

Rated power: 10W

Speaker size: 57MM

Battery: 3.7V/1500mAh

Play time: 8Hrs (50% volume)

Charging time: 4Hrs

Support: BT, TWS, TF, hands-free calls, FM

Bluetooth range: 10M

Input voltage: DC5V/1A

Charging port : Type-C

Product size: 100 X 138mm

Material: ABS+PC

7

**Precaution**

1. Please follow the instructions to operate.
2. Please charge the product with input power of or below 5V/1A, in order to protect the battery;
3. Please do not use this product near water. Do not immerse this product in any liquid or splash any liquid on this product.
4. Please store or use the product in a normal temperature environment.
5. Please keep the product away from heat source, such as radiators, hot air regulators, stoves, or other heat generating instruments.
6. Don't jam the ports of the product, such as charger port, LED port and microphone etc.

Warranty period: 1 Year

In case of consumer complaints:

Toll free number - 1800 22 8495

Email: sales@igear.asia

(Between 10am to 5pm, Mon-Fri)

8