



Congratulations
on purchasing your new VTech product.
Before using this baby monitor, please read the **Important safety instructions**.

VfEch 5" Smart Wi-Fi 1080p Video Monitor allows you to stay close to your baby when you are on the move or away. This monitor is Wi-Fi enabled, using your home wireless network to stream live video and audio through the 1080p baby unit and 5-inch colour screen parent unit. It allows you to maintain a constant connection to your baby.


You can also monitor from your smartphone or mobile tablet.

VfEch 5" Smart Wi-Fi 1080p Video Monitor uses **MyVfEch Baby Pro** app to let you instantly see and hear what's happening with your baby from anywhere in the world. The app can be downloaded from the App Store or the Google Play® Store.

[illegible]

- [illegible]

baby monitor package contains the following items. Save your sales receipt and original packaging in the event warranty service is necessary.



For mobile access:	
MyVTech Baby Pro mobile app	
Network	Wi-Fi
Wi-Fi router	2.4GHz 802.11 b/g/n
Internet connection	1.5 Mbps @ 720p or 2.5 Mbps @ 1080p upload bandwidth per baby unit


- 1 Download the free **MyTech Baby Pro** mobile app and install it to a mobile device, then use your mobile device and the mobile app to monitor your baby remotely.
 1. Press **MENU/SELECT** when the parent unit is idle.
 2. Go to - **Connect Mobile Phone**.
 3. Scan the QR code in the parent unit to download the app into your mobile device if you have not installed the app yet.
 4. Follow the instructions in the mobile app to set up and pair your baby unit to the mobile app.

- Alternatively, you can download the mobile app from the App Store or Google Play store.
- Install MyTech Baby Pro mobile app**
1. Browse the App Store  or the Google Play store .
 2. Search for the mobile app with the keyword "mytech baby pro".
 3. Download and install the **MyTech Baby Pro** mobile app to your mobile device.
- Scan the QR codes on the right to get the app.
- 

- Note**
- Make sure your mobile device meets the minimum requirement for the mobile app.
- Minimum requirement**
- The mobile app is compatible with:
- Android 5.0 or later;
 - iOS 12 or later.
- 2** After installing the mobile app, follow the instructions in the mobile app and parent unit to set up and pair your baby unit.
- In your mobile device:**
1. Tap  to run the mobile app in your mobile device, and then create a user account.
 2. We recommend that you use common web-based services, such as Google (Email for your baby's user account). Check your email (and Spam folders), and activate your new camera account via the email link, then sign in to your account.
 3. Follow the instructions in the mobile app to pair the camera. Tap **Add Camera** in the mobile app to start pairing.

Baby unit overview

- 1 Light sensor
- 2 Camera lens
- 3 Infrared LEDs
 - Allow you to see clearly in a dark environment
- 4 Microphone
- 5 Night Light
 - **Night Light Control Key**
 - Go to Night Light section to learn more
- 7 **ON/OFF switch**
 - Power it on or off.



- 1 **LINE LED light**
 - On when the parent unit is linked to the baby unit.
 - Flashes when the link to the baby unit is lost.
- 2 **CD LED light**
 - On when the parent unit is connected to AC power, and the battery is charging.
 - Flashes when the parent unit battery is low and needs to be recharged.
- 3 **Level-sound indicator light**
 - Green: low sound level is detected by baby unit.
 - Green and amber: moderate sound level is detected by the baby unit.
 - Green, amber and red: high sound level is detected by the baby unit.
- 4 **TALK /**
 - Press and hold to talk to the baby unit.
 - While in a sub-menu, press to exit.
- 5 **MENU / SELECT**
 - Press to enter the main menu.
 - While in a menu, press to choose an item, or save a setting.
- 6 **<A> / >A> Arrow keys**
 - Press to navigate left, right, up, and down within the main and sub-menus.
 - While viewing a zoomed image, press to move the viewed image left, right, up, and down.
- 7 **Microphone**
- 8 **VOL +/- VOL +**
 - Increase or decrease parent unit volume.
- 9 **Q Zoom**
 - Press to zoom in/out.
 - While in a sub-menu, press to view help menu.
- 10 **Power / LCD ON/OFF**
- 11 **Antenna**
- 12 **Speaker**
- 13 **Power jack**
- 14 **RESET**
 - Press to force reboot the parent unit.

 The document is a page from a book, showing a page number '10' in the top left corner. The page contains a large, stylized illustration of a person's head and shoulders, facing right. The person has dark, curly hair and is wearing a dark, high-collared garment. The background is a light, textured surface. The page is numbered '10' in the top left corner.

- Viscen asks about the privacy and peace of mind. That's why we've put together a list of industry-recommended best practices to help keep your wireless connection secure and your devices protected from unauthorized access. We've also included some helpful links and resources to consider consulting with the following tips.
- Ensure your wireless connection is secure:
 - Before installing a device, ensure your router's wireless signal is encrypted by selecting the "WPA2" or "WPA3" option in your router's settings.
 - Change default settings:
 - Change the default SSID in your router's settings to something unique to your network.
 - Change default passwords to unique, strong passwords. A strong password:
 - Is at least 12 characters long.
 - Is complex.
 - Contains a mix of uppercase letters, lowercase letters, special characters and numbers.
 - Keep your devices up to date:
 - Download updates from manufacturers so as they become available. This will ensure you always have the latest security updates.
 - If the feature is available, enable automatic updates for future releases.
 - Disable Unused Plug and Play (UPnP) on your router:
 - UPnP enabled on a router can limit the effectiveness of your firewall by allowing other network devices to connect to your network without your knowledge or approval from you. As a result, other malware programs could use this function to compromise security for the entire network.
- For more information on wireless security, visit our website for more details, including the following resources from industry experts:
 1. Federal Communications Commission (FCC) Wireless Connections and Bluetooth Security Tips - <https://www.fcc.gov/consumers/guides/wireless-connections-and-bluetooth-security-tips>
 2. U.S. Department of Homeland Security: Before You Connect a New Computer to the Internet - <https://www.dhs.gov/section-8714601>
 3. Federal Bureau of Investigation: Using IP Camera Safely - <https://www.fbi.gov/consumers/using-ip-camera-safely>
 4. Wi-Fi Alliance: Discover Wi-Fi Security - <https://www.wi-fi.com/en-us/learn-network/wi-fi-essentials/learn-wi-fi-security>

Connect the baby monitor

NOTES

The rechargeable battery in the parent unit is built in. We only use power adapters supplied with this product.

Make sure the parent unit and the baby unit are not connected to the switch-controlled electric outlets.

Connect the power adapter in a vertical or front position. The adapter prong are not designed to hold the weight of the parent unit and the baby unit. Do not connect them to any ceiling under the table, or cabinet outlet. Otherwise, the adapter may drop properly connected to the outlets.

Charge the parent unit battery before you use

The parent unit runs on rechargeable battery or AC power. To continuously monitor your baby, keep the parent unit connected to AC power.

NOTES

- Before using the baby monitor for the first time, charge the parent unit battery for 22 hours. When the parent unit battery is fully charged, the battery icon becomes solid.
- The standby time varies depending on your actual use.

After the parent unit is fully charged, press **POWER** until the welcome screen appears.

The battery icon indicates the battery status (see the following table):

BATTERY INDICATORS	BATTERY STATUS	ACTION
 and 	The battery has very little charge and may be used for only a short time.	Charge without interruption (about 30 minutes).
	The battery is fully charged.	To keep the battery charged, connect it to AC.

NOTE:
After powering up, the baby unit status LED will turn on and then turn off after a short time.
The status LED is set to off by default. If you want to turn the LED on, press **MENU**, then go to **STATUS LED** and turn it on.

NOTE:
Camera lens and surface may get warm during normal operation.

power when in use.

Raise the parent unit antenna for better reception

The diagram illustrates the status LED on the baby unit and the parent unit antenna. On the left, a baby unit is shown with a status LED that is lit. Below it, a close-up of the LED is shown with a label 'STATUS LED' and a note 'Turn the LED on'. On the right, a parent unit is shown with its antenna raised. A label 'Raise the parent unit antenna for better reception' points to the antenna.

Main Menu	Options	Main Menu	Options
Monitoring mode (For RM5756HD-2 only)		General settings	
	- View baby units in Single mode. - View baby units in Patrol mode. - View baby units in Split screen.		- Configure Wi-Fi - Change Wi-Fi Network - Selection Connection Mode - Connection Status - Connect mobile phone. - Reset Settings to factory default - Software Update
Night light	- Turn on or turn off night light. - Select a night light color.		

- Adjust night light brightness.
- Set a night light timer.

Melodies and soothing sounds

- Select play all melodies, or play one of the five melodies and five soothing sounds.
- You can also set the timer to stop playing after 15, 30 or 60 minutes, or playing non-stop.

Alerts - Sound, motion and temperature

Status icons

- Direct mode
Parent unit, baby unit 1 and baby unit 2
(For RM3756HD-2 only) are connected to each others directly.
- Wi-Fi Router mode
Parent unit, baby unit 1 and baby unit 2
(For RM3756HD-2 only) are connected to Home Wi-Fi network.

- **Sound settings**
 - Turn on/off sound and motion detection alerts.
 - Turn on/off sound and minimum temperature for alert range.
 - Turn on/off temperature alert.
 - Turn on/off Auto Wake Up function.
- **Parent unit settings**
 - Adjust parent unit screen brightness.
 - Adjust Low Battery Alert tone.
 - Adjust No Link Alert tone.
 - Turn on/off Dim mode.
- **Baby unit settings**
 - Turn on/off Night Vision.
 - Turn on/off parent unit Status LED.
 - Adjust baby unit speaker volume.

 Baby unit 1 and 2 and baby sleeping in **Sleep mode (7 or RM35T5HD-0 only)**.

 Night vision is turned on.

 Motion detection alerts is turned on.

 Sound detection alerts is turned on.

 Melodies and soothing sounds are playing.

 Night light is turned on.

 Auto night light brightness is activated.

 Temperature alert is turned on.

 Parent unit is muted.

 Temperature is lower than 68°F.

 Temperature is within 68°F and 75°F.

 Temperature is higher than 75°F.

To ensure that your baby monitor is always at its best performance, the parent unit will prompt you to update its software and the baby unit firmware when there are new versions available.

- Follow the instructions on the parent unit screen to update your baby monitor. If you skip the updates, the parent unit and baby unit will be updated automatically when the parent unit is powered off, and then powered on again.
- To check if your device is running on the latest software or to update your device software, go to

 > **Software Update**

Connect your baby monitor to Wi-Fi

- You must connect your video monitor to your secured home Wi-Fi network in order to receive the latest software and firmware updates. To set it up, go to:

 > **Configure Wi-Fi**

You can control the night light remotely on the parent unit or directly on the baby unit.

On the parent unit:

1. Press **MENU**.
2. Press **◀** or **▶** to scroll to **Night Light** menu, then press **MENU** or **▶** to enter.
3. Press **◀** or **▶** to choose below options:

- Turn on/off night light
- Change night light color
- Adjust night light brightness
- Set night light timer

On the baby unit:

 Night Light Control Key

Single Tap: Turn on/off
Tap and hold: Adjust night light brightness

